

Project:		
Fixture Type:		
Location:		
Contact:		

One-Light Outdoor

Ceiling flush mounted • Damp location listed PROGRESS LED

Description:

6" flush mount cylinder. The P5741 Series are ideal for a wide variety of interior and exterior applications including residential and commercial. The Cylinders feature a 120V alternating current source and eliminates the need for a traditional LED driver. This modular approach results in an encapsulated luminaire that unites performance, cost and safety benefits.

Specifications:

- · Metallic Gray (-82) (powder coat paint)
- · Die cast and extruded aluminum Construction
- · Ideal for a wide variety of interior and exterior applications.
- · Die-cast aluminum construction with durable powder coated finish
- · 1295 lumens 44 lumens/watt
- 3000K color temperature, 90+ CRI
- Dimmable to 10% brightness (See Dimming Notes)
- Unit covers a standard 4" octagonal recessed outlet box
- · Mounting strap for outlet box included
- · 6" of wire supplied
- · Meets California Title 24 high efficacy requirements for outdoor use only

Performance:

Number of Modules	1	
Input Power	29.4w	
Input Voltage	120 V	
Input Frequency	60 Hz	
Lumens/LPW (Delivered)	1122/38.1 (LM-79)	
CCT	3000 K	
CRI	90 CRI	
Life (hours)	60,000 (L70/TM-21)	
FCC	FCC Title 47, Part 15, Class B	
Min. Start Temp	-30 °C	
Max. Operating Temp	30 °C	
Warranty	5 year warranty	
Labels	cCSAus Damp location listed	
	Meets California Title 24 high efficacy requirements	
	for outdoor use only	

P5741-82/30K

Images:



Dimensions:

Diameter: 6" Height: 12"



One-Light Outdoor

Ceiling flush mounted • Damp location listed PROGRESS LED

P5741-82/30K

Dimming Notes:

P5741 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Diva DVELV-300P

Lutron Nova NTELV-300

Lutron Vierti VTELV-600

Lutron MAELV-600

Lutron SPELV-600

Leviton AWRMG-EAW

Leviton 6615-P

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.