

## Medium Wall Lantern

Wall mounted • Wet location listed



### Description:

LED wall lantern with etched umber linen glass. Includes dark sky shield for full cut-off illumination or remove for a traditional lighting effect. 120V AC replaceable LED module, 1,211 lumens 71.2 lumens/watt per module (source). 3000K color temperature and 90+ CRI.

### Specifications:

- Antique Bronze (-20) (powder coat paint)
- Aluminum Construction
- Etched UMBER LINEN glass cylindrical diffuser
- LED Module is replaceable (part # 93053641)
- Etched umber linen glass.
- Includes removable dark sky shield for full cut-off illumination.
- Powder coated finish.
- 1,211 lumens 71.2 lumens/watt per module (source)
- 3000K color temperature, 90+ CRI.
- Dimmable to 10% brightness (See Dimming Notes)
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- ENERGY STAR® qualified
- Meets California Title 24 high efficacy requirements for outdoor use only

### Performance:

Number of Modules	1
Input Power	17w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW (Source)	1211/71.2 (LM-82)
Lumens/LPW (Delivered)	234/14.1 (LM-79)
CCT	3000 K
CRI	90 CRI
Life (hours)	60,000 (L70/TM-21)
FCC	Meets FCC Title 47, Part 15 Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Wet location listed ENERGY STAR® qualified Meets California Title 24 high efficacy requirements for outdoor use only

## P6085-2030K9

### Images:



### Dimensions:

Width: 9"  
Depth: 10-1/2"  
Height: 12-1/2"  
H/CTR: 3-1/8"

Glass  
Width: 5-5/16"  
Height: 7-3/8"

## P6085-2030K9

### Dimming Notes:

---

P6085 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

### Dimming Controls

---

Lutron Nova T NTELV-300

Lutron Vienti VTELV-600

Lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Leviton Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.